

CTL+Q EDIT or DEL LAST QSO
CTL+K TYPE AHEAD CW BUFFER
CTL+G ACTIVITY GRAPH

CTL+M SECTION MAP
CTL+N NETWORK STATUS
CTL+T STATISTICS

SPACE or TAB ADVANCE FIELD
ALT+O OPERATOR INFO
ALT+C CLEAR QSO INFO

ESC – STOP SENDING
▲ – INCREASE SPEED
▼ – DECREASE SPEED

--- RUN MODE ---			SHOOT & POUNCE MODE										
CQ	EXCHG	TU/QRZ	K8BF		EXCHG	CLASS?	SEC?	4A 4A		OH OH	4AOHx2	AGN?	KB SEND

N3FJP Entry Area

Call	Class	Section
<input type="text"/>	<input type="text"/>	<input type="text"/>

FIELD DAY 2017 CW OPERATION TUTORIAL

GENERAL: There are two operating modes:

RUN MODE: Stay on one frequency calling CQ, working callers as they come to you.

SHOOT & POUNCE: Tuning across the band, working new stations as you find them.

[Refer to the above F-KEY template which will be on the top of the keyboard at field day and the N3FJP on-screen entry area sample above]

RUN PROCEDURE:

Press **F1** to call CQ. Repeat until you are called.

Enter call sign in CALL box, then press **F2** to send our information.

Enter his CLASS and SECTION in boxes, then press **F3** to confirm contact and automatically log this contact.

Repeat.

SHOOT & POUNCE:

Find a station calling, enter his call sign in CALL box. If a dupe, move on. If not a dupe, press **F4** to send our call.

When he responds to your call, enter his CLASS and SECTION in the boxes and press **F5** to send our information and log the contact.

Repeat.

If you need a repeat of callers CLASS press **F6**; of his SECTION, Press **F7**; for complete repeat of his information, press **F11**

If caller asks for repeat of our CLASS press **F8**; of our SECTION, Press **F9**; our CALL press **F4**; if he is having extreme difficulty, press **F10**

BE SURE TO USE CTL+O COMBINATION TO CHANGE OPERATOR AND LOGGER CALL WHEN YOU CHANGE OPERATORS!